

FM TRANSMITTER 20-40 W

Specification	Value
Low-Power Output Power	30 W
Frequency Range	87.5-108 MHz
Frequency Step	100 KHz (BCD Switch)
MPX Input Connector	BNC
Pilot	19 KH \pm 1HZ
Audio Frequency Response	\pm 0.5 dB (50 Hz – 15Khz)
15 Khz Filtering	> 40 dB at 19Khz
Stereo Separation	> 40 dB
Audio Input Connector	XLR (Balanced)
Audio Distortion	< %1
Pre – emphasis	50 μ s / 75 μ s – On(Off)
Clipping	On / Off
Limiting	On / Off
Audio Input Level	-5 dB -+10 dB

